

Barkhausen-like conductance noise in polycrystalline high Tc superconductors immersed in a slowly varying magnetic field.

P.Mazzetti, A.Stepanescu and P.Tura

Istituto Nazionale per la Fisica della Materia, Unità di Ricerca del Politecnico di Torino, and Dipartimento di Fisica, Politecnico di Torino, Corso Duca degli Abruzzi 24, I-10129 Torino, Italy

A.Masoero

Istituto Nazionale per la Fisica della Materia, Unità di Ricerca del Politecnico di Torino, and Dipartimento di Scienze e Tecnologie Avanzate, Università del Piemonte Orientale 'Amedeo Avogadro' C.so Borsalino 54, I-10131 Alessandria, Italy

I.Puica

Catedra de Fizica, Universitatea Politehnica Bucuresti, Spl. Independentei 313, Bucharest, Romania
(February 1, 2008)

Analysis of the resistive transition of a polycrystalline YBCO specimen produced by an a.c. magnetic field, reveals the presence of a large conductance noise signal which is repetitive over subsequent magnetization cycles. It is shown that the noise arises from avalanche effects produced by the simultaneous resistive transition of large groups of weak links. Owing to its repeatability, the noise signal may be considered a sort of signature of the weak links critical current distribution, making it an interesting new tool for the study of high Tc ceramic superconductors, as reported measurements of noise hysteresis show.

PACS: 72.70.+m, 74.40.+k

The resistive transition of polycrystalline high Tc superconductors is, in general, dominated by the inter-grain layers, which behave as shunted Josephson junctions (weak links). The weak link ensemble, on the other side, is characterized by a distribution of critical currents which depends on the local value of the magnetic field. When the specimen is crossed by a d.c. current and immersed in a slowly increasing magnetic field, there are gradual transitions to the resistive state of the weak links and, above a given threshold, the whole specimen becomes increasingly resistive. As shown by the reported experiments, this process is not smooth, but is characterized by a large noise. It is very interesting to notice that the noise signal represents a sort of signature of the local distribution [1] of the weak-link critical currents, since it is *repetitive* over different magnetic field cycles, until a magnetic perturbation, strong enough to change such a distribution by effect of flux trapping within the superconducting grains, is applied.

Another important aspect of this noise, which has a completely different origin of the noise observed in stationary conditions [2 – 6], concerns the fact that it is produced by strong correlations during the transition of the weak-links, giving rise to avalanche effects, similar to those observed in the Barkhausen noise of ferromagnets. As computer simulations show, these avalanches correspond to abrupt rearrangements of the internal current distribution, and thus of the distribution of superconducting and resistive weak-links, due to the need of satisfying Kirchhoff equations in a network of highly non linear circuit elements. The step-like variation of the specimen

conductance in correspondence to each weak-link transition avalanche gives rise, as reported in the following, to a $1/f^2$ power spectrum, as opposed to the $1/f$ spectrum observed in the stationary case [7]. Also the amplitude of the noise, which is orders of magnitude larger than expected in the case of uncorrelated transition of the individual weak links, confirms the presence of these avalanche effects.

Another important aspect, also confirmed by computer simulations, concerns the fact that the position along the time axis and the amplitude of these steps, when the magnetic field is varied, is strongly dependent on the local distribution of the weak-link critical currents. Thus the detection and storing of the noise signal within a given field interval along the loop allows to observe very small variations of such a distribution, produced by external perturbations. For instance, as shown in the following, small hysteretic effects, invisible on the conductance vs. field plot, may be evidenced by comparing the noise signals detected in the same field interval along a loop when the field is increasing or decreasing. It should be noticed that the repeatability of the noise signal during cycling is a very rare property of a physical system, and reflects an intrinsic non-fluctuating aspect of the nature of the system itself. In the case of the Barkhausen noise, for instance, the noise signal is in general not repetitive over different cycles, since it is determined during each cycle by the domain configuration obtained in the preceding one [8].

Experiments were performed on a YBCO specimen suitably treated to lower the weak-links critical currents.

This treatment made the specimen very sensitive to low magnetic fields and allowed to use small, noise free a.c. magnetic fields to perform the experiments. The use of small fields was also needed to avoid flux penetration within grains, such that only the weak-links were involved in the resistive transition of the specimen. Noise was detected by using a 4 contact technique on a small cylindrical specimen 1mm in diameter and 10mm in length. An extra low noise input transformer was used to match the input impedance of the preamplifier and to cut the d.c. component of the noise signal. It acted as a band-pass filter in the range between 5Hz and 10kHz. A standard electronic set-up was used to digitally storing the signal in a selected field interval during cycling.

Fig.1 shows three samples of the noise signal detected within the same field interval when looping and the background noise when the field is kept constant. The repeatability of the noise signal before the application of the magnetic perturbation is quite evident. Small changes are mainly due to the superimposed background noise.

In Fig.2 the power spectra of the noise obtained during field variation and in a steady state condition are reported. The near $1/f^2$ behaviour of the spectrum in the first case is consistent with the assumption that the noise is constituted by the superposition of random step-like variation of the specimen conductance. The cut-off frequencies of the input transformer had the effect of limiting the frequency range over which the noise spectrum could be detected. They had also the effect of transforming the voltage steps into exponential pulses, a fact that explains why the noise signals looks like those reported in Fig.1.

These results suggest that the presence of abrupt discontinuous conductance changes in a network of non linear resistors, having current-voltage characteristics similar to the ones of Josephson junctions, be a general property of this type of networks. This fact is confirmed by computer simulations, as reported in the following. Below the critical temperature of the grains, the polycrystalline superconductive sample is modelled as a rectangular three-dimensional array of intergranular weak links, fed with constant d.c. current flowing between two plane electrodes applied on the opposite faces. Any individual weak link is viewed as a nonlinear circuit element which is in a superconducting state for local currents below a certain critical value i_c and in a normal resistive state for currents above this value (see Fig.3). Its critical current value depends in turn on the temperature and on the local intergranular magnetic field B_i . We used standard relations [9 – 12] to determine the dependance of the weak-link critical current i_c on the local field value B_i , which, owing to the screening effect of the superconducting grains, is always tangent to the weak-link surface and depends on the angle θ between the applied field $\mathbf{B}$ and the normal $\mathbf{n}$ to the weak-link surface. In the calculations, whose details will be given in another paper, the relation between the local intergranular field B_i and the

applied field B was assumed to be of the form

$$B_i = K \cdot B |\sin \theta| \quad (1)$$

where K is a flux compression factor due to the flux exclusion within the superconducting grains. The large spread of the values of θ gives rise to a large distribution of critical currents i_c , whose average value depends on the modulus of the applied field B . In the calculations the values of the local angle θ were set by considering an uniform solid angle distribution for the junction orientations. Kirchoff's equations for potentials and currents, together with the weak-link current-voltage characteristic, provided a set of coupled nonlinear equations for the electric potentials at the nodes of the network, which were solved by an iterative method. At each iterative step, from the previous set of node potentials, the junction conductances were actualized according to the nonlinear current-voltage characteristic described above. Considering then these conductances as constant, the linear equation system given by Kirchoff's law is solved, so that a new set of node potential is found. The calculation technique, a modified algorithm based on the method of the conductance matrix, is described in ref. [6]. The iterative cycle ends when the difference between two consecutive sets of node potentials becomes sufficiently small with respect to their actual values. We used in our simulations a relative tolerance of the order of 10^{-7} . Results corresponding to two different actualization of the same distribution of junction critical currents in a cubic network of about 1000 junctions are reported in Fig.3. Several checks were made to ensure that the steps were not an artifact of the numerical calculations by increasing the point density and by reducing the relative tolerance for exiting the iteration loop. For what concerns this tolerance, it was observed that the position of the steps depends on this quantity when its value is not low enough, but that their position and amplitude becomes stable when it is assumed to be sufficiently small ($<10^{-6}$). It was also observed that the position of the steps along the field axis is very sensitive to small changes in the assumed distribution of the critical currents, a fact that is typical of the presence of instabilities in a complex system. The high sensitivity of the noise signal to even small variations of the local distribution of the weak link critical currents allows to use this quantity as a test for evidencing effects that would not be detectable by other means. We present here some experimental results that clearly show the presence of magnetic hysteresis in the YBCO specimen described above, even when it is submitted to an a.c. magnetic field whose amplitude is so small that hysteresis cannot be detected by conventional means.

In this experiment the specimen was submitted to an a.c. field of a few Gauss of amplitude and crossed by a d.c. current of a few mA. Fig.4 represents the behaviour of the electrical resistance of the specimen vs. magnetic field. It appears to be completely reversible and without

evident hysteresis. Fig.5 shows the noise signal detected in a small field interval during cycling. It is evident that the noise signal, which is repetitive over subsequent cycles, is quite different along the increasing or decreasing branch of the loop, even if the field interval where the signal is detected is the same. This fact proves the presence of hysteresis, probably due to some magnetic flux trapping along the cycle. This effect could also be related to an intrinsic hysteresis of the v-i characteristic of each individual weak link, a possibility which, however, was not taken into account in the computer simulations. In this case it was tested that a complete reversibility is obtained. From the experimental point of view, it should however be possible to distinguish between flux trapping and hysteresis of the individual weak link characteristics by performing experiments similar to the reported ones, but progressively reducing the field amplitude to see if noise tends to become reversible. It may be noticed that measurements performed on what could be considered a single weak link, i.e. the grain boundary junction of a bicrystal of BSCCO [13] and a submicron grain boundary junction in YBCO thin films [14] show Josephson like characteristics but no hysteretic effects were reported by the authors. In any case it seems clear that the noise could be used to investigate this and other aspects of the resistive transition of granular superconducting materials. A more complete analysis of the effect on the noise signal of field amplitude, frequency, temperature and d.c. current will be the argument of an extended paper. Here we want to stress that the noise signal, being an highly structured quantity, allows to evidence even very small changes of the weak link critical current distribution. Its repeatability over different magnetization cycles allows to depurate it from the background noise through a simple averaging procedure, making it an interesting new tool to analyze the physical properties of polycrystalline HTCS. Measurements on different materials, either bulk or thin films, might reveal important aspects of the physics of these superconductors, related to their granular structure. At the moment no checks were made to see what happens in monocrystalline bulk or thin films HTCS.

-
- [1] With "local distribution", as opposed to "statistical distribution" we intend a particular actualization of the statistical distribution over an ensemble of ordered elements.
- [2] W.N. Kang, D.H. Kim, J.H. Park, T.S. Hahn, S.S. Choi and K.E. Gray, *Physica C* **233**, 402 (1994)
- [3] M. Kawasaki, P. Chaudhari and A. Gupta, *Phys. Rev. Lett.* **68**, 1065 (1992)
- [4] R.D. Black, L.G. Turner, A. Mogro-Campero, T.C. McGee and A.L. Robinson, *Appl. Phys. Lett.* **55**, 2233 (1989)
- [5] A.H. Miklich, J. Clarke, M.S. Colclough and K. Char,

Appl. Phys. Lett. **60**, 1899 (1992)

- [6] L. Cattaneo, M. Celasco, A. Masoero, P. Mazzetti, I. Puica and A. Stepanescu, *Physica C* **267**, 127 (1996)
- [7] A $1/f^2$ power spectrum can be considered as the limit of a lorentzian spectrum when its cut-off frequency tends to zero. It is the case of the power spectrum of a train of Poisson distributed exponential pulses whose decay time tends to ∞ (steps).
- [8] J.R. Petta, M.B. Weissman and G. Durin, *Phys. Rev. E* **56**, 2776 (1997)
- [9] K.H. Müller, M. Nikolo and R. Driver, *Phys. Rev. B* **43**, 7976 (1991)
- [10] V. Ambegaokar and A. Baratoff, *Phys. Rev. Lett.* **10**, 486 (1963)
- [11] R. Gross and B. Mayer, *Physica C* **180**, 235 (1991)
- [12] A. Marx and R. Gross, *Appl. Phys. Lett.* **70**, 120 (1997)
- [13] A. Marx, U. Fath, W. Ludwig, R. Gross, T. Amrein, *Phys. Rev. B* **51**, 6735 (1995)
- [14] F. Herbristrit, T. Kemen, L. Alff, A. Marx and R. Gross, *Appl. Phys. Lett.* **78**, 955 (2001)




FIG. 1. Voltage noise measured on the HTCS specimen crossed by a current of 6.4 mA and immersed in an a.c. triangular magnetic field of amplitude 3.2 G and frequency 0.08 Hz. Curves #1, #2, #3 show the noise taken on the same field interval between 0÷0.4 G over different cycles. Curve #0 shows the background noise when the field is kept constant. The similarity of curves #1, #2 shows that roughly the same processes giving rise to the noise occur at the same values of the field when no large magnetic perturbations are applied to the specimen. Curve #3 shows the effect of the momentary application of a magnetic field of a few tens of Gauss. The variation of the noise signal is attributed to a permanent change of the critical current distribution caused by flux trapping within the superconducting grains.




FIG. 2. Power spectra of the noise generated by an a.c. magnetic field of 3.2 G amplitude and 0.08 Hz frequency (curve b) and of the noise obtained when the field is kept constant (curve a). Curve (a) has been subtracted from the spectrum obtained in the presence of the a.c. field to obtain curve (b), which thus represents the pure contribution to the noise of the a.c. field. The nearly $1/f^2$ slope of this curve is typical of the spectrum of a noise constituted by a series of randomly distributed steps. Dotted lines represent the $1/f$ and $1/f^2$ slopes. Below 5 Hz the data have been corrected by using the cut-off frequency curve of the input transformer.




FIG. 3. Results of a simulation of the behavior of the electrical resistance of the YBCO specimen under a varying magnetic field. The simulation refers to a 3-Dimensional cubic network of about 1000 nonlinear resistor elements having a i-v characteristic schematically represented in the inset. The two curves are different simulations corresponding to different actualization of the same distribution of critical currents obtained by changing the sequence of the pseudo-random numbers generated by the computer. For a comparison with the results reported in Fig.1 and Fig.2, account should be taken that the input transformer cut the d.c. component of the signal and changes the steps into exponential pulses.




FIG. 4. Electrical resistance behaviour vs. magnetic field, of the HTCS specimen crossed by a d.c. current I slightly higher than its critical current at zero field. The figure shows that the specimen resistance, in addition of being very sensitive to the magnetic field, does not present any visible hysteretic effect. However analysis of the noise signal allows to evidence that some type of hysteresis as actually taken place.




FIG. 5. Noise signals detected within the same field interval of 0.4 G during cycling as in Fig.1. Curves #1 and #2 are taken when the field is increasing and curves #3 and #4 when the field is decreasing. The change of the noise shape evidences the presence of a magnetic hysteresis which changes the weak links critical current distribution. This hysteresis is so small that it cannot be evidenced by direct measurements (see Fig.4).